




Software Manual NV Image Tool

Rev. 1.00

GTP-250II



<http://www.senortech.com>

■ Table of Contents

1. Manual Information.....3

2. Usage Environment3

 2-1 Operating System3

 2-2 Device Property3

3. Ready to NV Image Tool3

4. Usage of NV Image Tool4

 4-1 Communication Configuration4

 4-2 Image List Management5

 4-3 Change Color.....6

 4-4 Download the Image6

 4-4-1 Download the color image in thermal printer7

 4-4-2 Download the mono image in thermal printer8

 4-5 Print the NV Image9

1. Manual Information

The purpose of this manual is to provide information on the operation and usage instructions of the NV Image Tool for the SENOR Tech GTP-250II Printers. This program helps you to download user-defined images to the flash memory in the printer and to recall and print those images with fast speed.

2. Usage Environment

2-1 Operating System

Following operating systems are supported for usage.

Microsoft Windows XP
Microsoft Windows 2003 Server
Microsoft Windows Embedded For Point Of Service
Microsoft Windows Vista
Microsoft Windows 7

2-2 Device Property

Use of this Utility is supported on the following property.

Model	Serial	Parallel	USB	Ethernet	Capability	Downloadable Image Count	Color Support
GTP-250II	O	O	O	O	256Kb	10	Mono / 2Color

O: Supported

3. Ready to NV Image Tool

NV Image Tool is included in the enclosed CD, and can also be downloaded from the SENOR Tech website.

www.senortech.com


The Name of Execute File is "NVTool.exe".

4. Usage of NV Image Tool


4-1 Communication Configuration

To use the NV Image Tool, It is necessary to set the status of communication between Printer and PC.

- 1) Run the “NVTool” file.
- 2) Upon initiation of the program, the following pop-up window will appear.



- 3) Click the Configuration button to set communication configuration.




4) Each printer model has different communication interface. Set the port and the communication configuration that corresponds to the printer

***In the Serial Interface, match the communication setting (COM Port Number and Baud Rate) to those of the Printer.**

5) After selecting the configuration press OK to complete the communication configuration setting, and press Cancel to cancel the configuration selected.


4-2 Image List Management

User can open/add, delete and reset images with three buttons in Bitmap selection. Only **bmp** type of image is available to download.




4-3 Change Color

User can change the color of image, when you use two color printers. Just try to move the horizontal scroll bar as you can see in the picture.




4-4 Download the Image

When the "Download.." button is clicked, pop-up window and the steps are different based on printer model.



4-4-1 Download the color image in thermal printer




1) Click the "Auto Address Download" button to download the Image to the Printer, and a window appears, which displays the progress of downloading.


* All the images in the printer will be erased, and New images in the program will be downloaded.

* User can save color-converted image to PC using the "Save File.." button.

2) After the font download is complete, the following message will appear.




4-4-2 Download the mono image in thermal printer



1) Click the “Download Start” button to download the Image to the Printer, and a window appears, which displays the progress of downloading.

2) After the font download is complete, the following message will appear.



4-5 Print the NV Image

By Pressing the “Print” button, User can print all the image(s) in flash memory.

